

UM1907 User manual

Discovery kit for STM32F7 series with STM32F746NG MCU

Introduction

The 32F746GDISCOVERY Discovery kit is a complete demonstration and development platform for the STMicroelectronics Arm[®] Cortex[®]-M7-core-based STM32F746NG microcontroller (STM32F746NGH6 order code). This microcontroller features four I²Cs, six SPIs with three multiplexed simplex I²S, SDMMC, four USARTs, four UARTs, two CANs, three 12-bit ADCs, two 12-bit DACs, two SAIs, 8- to 14-bit digital camera module interface, internal 320+16+4-Kbyte SRAM and 1-Mbyte flash memory, USB OTG_HS and FS, Ethernet MAC, FMC interface, quad-SPI interface, SWD debugging support. This Discovery kit offers everything required for users to get started quickly and develop applications easily.

The full range of hardware features on the board helps users to evaluate almost all peripherals (USB OTG_HS and FS, 10/100-Mbit Ethernet, microSD[™] card, USART, SAI audio DAC stereo with audio jack input and output, ST-MEMS digital microphones, SDRAM, quad-SPI flash memory, 4.3" color LCD-TFT with a capacitive multitouch panel, SPDIF RCA input, and others) and to develop their applications. ARDUINO[®] Uno V3 connectors make it possible to easily connect extension shields or a daughterboard for users' specific applications. The integrated ST-LINK/V2-1 provides an embedded in-circuit debugger and programmer for the STM32.

The 32F746GDISCOVERY board is provided with the STM32CubeF7 MCU Package, which offers an STM32 comprehensive software HAL library as well as various software examples.




Figure 1. 32F746GDISCOVERY board (top view: left side - bottom view: right side)

Pictures are not contractual.

September 2025 UM1907 Rev 6 1/46

Contents UM1907

Contents

| 1 | Feat | ures | 7 |
|---|------|---|----|
| 2 | Orde | ering information | 8 |
| | 2.1 | Codification | 8 |
| 3 | Deve | elopment environment | 9 |
| | 3.1 | System requirements | 9 |
| | 3.2 | Development toolchains | 9 |
| | 3.3 | Demonstration software | 9 |
| | 3.4 | EDA resources | 9 |
| 4 | Safe | ty recommendations | 10 |
| | 4.1 | Targeted audience | 10 |
| | 4.2 | Handling the board | 10 |
| 5 | Hard | lware layout and configuration | 11 |
| | 5.1 | The 32F746GDISCOVERY Discovery board layout | 12 |
| | 5.2 | 32F746GDISCOVERY Discovery board mechanical drawing | 14 |
| | 5.3 | Embedded ST-LINK/V2-1 | 15 |
| | | 5.3.1 Drivers | 15 |
| | | 5.3.2 ST-LINK/V2-1 firmware upgrade | 16 |
| | 5.4 | Power supply | 16 |
| | 5.5 | Programming/debugging when the power supply is not from ST-LINK (5V link) | 18 |
| | 5.6 | Clock sources | 19 |
| | 5.7 | Reset sources | 19 |
| | 5.8 | Audio | 19 |
| | 5.9 | USB OTG_FS | 20 |
| | 5.10 | USB OTG_HS | 20 |
| | 5.11 | microSD™ card | 20 |
| | 5.12 | Ethernet | 21 |
| | 5.13 | SDRAM memory | 21 |
| | | | |



| UM1907 | Contents |
|--------|----------|
| UM1907 | Contents |

| | 5.14 | Quad-SPI NOR flash memory | 21 |
|---|-------|--|----|
| | 5.15 | Camera module | 22 |
| | 5.16 | Display LCD-TFT | 22 |
| 6 | Conn | ectors | 23 |
| | 6.1 | I ² C extension connector CN2 | 23 |
| | 6.2 | Camera module connector P1 | 23 |
| | 6.3 | ARDUINO® Uno V3 connectors | 24 |
| | 6.4 | USB OTG_HS Micro-AB connector CN12 | 26 |
| | 6.5 | Ethernet RJ45 connector CN9 | 26 |
| | 6.6 | USB OTG_FS Micro-AB connector CN13 | 27 |
| | 6.7 | microSD™ connector CN3 | 28 |
| | 6.8 | ST-LINK/V2-1 USB Type-B connector CN14 | 28 |
| | 6.9 | Audio stereo speakers JP3 and JP4 | 29 |
| | 6.10 | Audio green jack (line out) CN10 | 29 |
| | 6.11 | Audio blue jack (line in) CN11 | 29 |
| | 6.12 | SPDIF input RCA connector CN1 | 29 |
| 7 | 32F74 | 46GDISCOVERY I/O assignment | 30 |
| 8 | 32F74 | 46GDISCOVERY information | 37 |
| | 8.1 | Product marking | 37 |
| | 8.2 | 32F746GDISCOVERY product history | 38 |
| | 8.3 | Board revision history | 40 |
| 9 | | ral Communications Commission (FCC) SED Canada Compliance Statements | 41 |
| | 9.1 | FCC Compliance Statement | 41 |
| | | Part 15.19 | 41 |
| | | Part 15.21 | |
| | | Part 15.105 | |
| | | Responsible party - U.S. contact information | |
| | 9.2 | ISED Compliance Statement | |
| | | Compliance Statement. | |
| | | Déclaration de conformité | 42 |
| | | | |

| Contents | UM19 | 907 |
|----------|------------------|-----|
| 10 | Product disposal | 43 |
| Revision | history | 44 |

UM1907 List of tables

List of tables

| Table 1. | List of available products | 8 |
|-----------|--|------|
| Table 2. | Codification explanation | 8 |
| Table 3. | I ² C extension connector CN2 | . 23 |
| Table 4. | Camera module connector P1 | |
| Table 5. | ARDUINO® connectors (CN4, CN5, CN6, and CN7) | 25 |
| Table 6. | USB OTG HS Micro-AB CN12 | |
| Table 7. | RJ45 connector CN9 | . 27 |
| Table 8. | USB OTG FS Micro-AB connector CN13 | . 27 |
| Table 9. | microSD connector CN3 | . 28 |
| Table 10. | USB Type-B connector CN14 | . 29 |
| Table 11. | SPDIF input RCA connector CN1 | . 29 |
| Table 12. | 32F746GDISCOVERY I/O assignment | 30 |
| Table 13. | Product history | |
| Table 14. | Board revision history | 40 |
| Table 15. | Document revision history | 44 |
| | | |



List of figures UM1907

List of figures

| Figure 1. | 32F746GDISCOVERY board (top view: left side - bottom view: right side) | 1 |
|------------|--|----|
| Figure 2. | Hardware block diagram | 11 |
| Figure 3. | 32F746GDISCOVERY Discovery board top layout | 12 |
| Figure 4. | 32F746GDISCOVERY Discovery board bottom layout | |
| Figure 5. | Mechanical drawing | 14 |
| Figure 6. | USB composite device | 15 |
| Figure 7. | JP1 (5V ext) from JP2 (5V) | |
| Figure 8. | JP1 (5V ext) from CN6 (Vin) | 16 |
| Figure 9. | JP1 (5V link) | 17 |
| Figure 10. | JP1 (usb_fs) | 18 |
| Figure 11. | JP1 (usb_hs) | 18 |
| Figure 12. | Inside RJ45 jack | 21 |
| Figure 13. | I ² C extension connector CN2 (front view) | 23 |
| Figure 14. | Camera module connector P1 (front view) | 23 |
| Figure 15. | USB OTG Micro-AB connector CN12 (front view) | 26 |
| Figure 16. | Ethernet RJ45 connector CN9 (front view) | 26 |
| Figure 17. | USB OTG Micro-AB connector CN13 (front view) | 27 |
| Figure 18. | microSD connector CN3 (front view) | 28 |
| Figure 19 | USB Type-B connector CN14 (front view) | 28 |

UM1907 Features

1 Features

 STM32F746NGH6 Arm[®] Cortex^{®(a)} core-based microcontroller with 1 Mbyte of flash memory and 340 Kbytes of RAM, in a BGA216 package

- 4.3" RGB 480×272 color LCD-TFT with capacitive touchscreen
- Ethernet compliant with IEEE-802.3-2002
- USB OTG HS
- USB OTG FS
- SAI audio codec
- Two ST-MEMS digital microphones
- 128-Mbit quad-SPI flash memory
- 128-Mbit SDRAM (64 Mbits accessible)
- Two user and reset push buttons
- Board connectors:
 - Image sensor
 - microSD™ card
 - RF-EEPROM daughterboard connector
 - 2×USB with Micro-AB
 - Ethernet RJ45
 - SPDIF RCA input connector
 - Audio line-in and line-out jack
 - Stereo speaker outputs
 - ARDUINO[®] Uno V3 expansion connectors
- Flexible power-supply options: ST-LINK, USB V_{BUS} or external sources
- Power supply output for external applications: 3.3 V or 5 V
- Comprehensive free software libraries and examples available with the STM32Cube MCU Package
- On-board ST-LINK/V2-1 debugger/programmer with USB re-enumeration capability: mass storage, Virtual COM port, and debug port
- Support of a wide choice of integrated development environments (IDEs) including IAR™, Keil[®], and STM32CubeIDE

arm

a. Arm and Cortex are registered trademarks of Arm Limited (or its subsidiaries) in the US and/or elsewhere.



UM1907 Rev 6 7/46

Ordering information UM1907

2 Ordering information

To order the 32F746GDISCOVERY Discovery kit, refer to *Table 1*. Additional information is available from the datasheet and reference manual of the target microcontroller.

Table 1. List of available products

| Order code | Board reference | Target STM32 | | |
|------------------|-----------------|---------------|--|--|
| STM32F746G-DISCO | MB1191 | STM32F746NGH6 | | |

2.1 Codification

8/46

The meaning of the codification is explained in Table 2.

Table 2. Codification explanation

| STM32F7XXY-DISCO | Description | Example: STM32F746G-DISCO |
|------------------|---|---------------------------|
| STM32F7 | MCU series in STM32 32-bit Arm Cortex MCUs | STM32F7 series |
| XX | MCU product line in the series | STM32F746 |
| Υ | STM32 flash memory size: – E for 512 Kbytes – G for 1 Mbyte | 1 Mbyte |
| DISCO | Discovery kit | Discovery kit |

The order code is mentioned on a sticker placed on the top side of the board.

3 Development environment

3.1 System requirements

- Windows® OS (7, 8 and 10), Linux® 64-bit, or macOS®(a)
- USB Type-A to Mini-B cable

3.2 Development toolchains

- Keil[®] MDK-ARM^(b)
- IAR™ EWARM^(b)
- STMicroelectronics STM32CubeIDE

3.3 Demonstration software

The demonstration software, included in the STM32Cube MCU Package corresponding to the on-board microcontroller, is preloaded in the STM32 flash memory for easy demonstration of the device peripherals in standalone mode. The latest versions of the demonstration source code and associated documentation can be downloaded from www.st.com.

3.4 EDA resources

All board design resources, including schematics, EDA databases, manufacturing files, and the bill of materials are available from the 32F746GDISCOVERY product page at www.st.com.

b. On Windows® only.



UM1907 Rev 6 9/46

a. macOS® is a trademark of Apple Inc. registered in the U.S. and other countries.

4 Safety recommendations

4.1 Targeted audience

This product targets users with at least basic electronics or embedded software development knowledge such as engineers, technicians, or students. This board is not a toy and is not suited for use by children.

4.2 Handling the board

This product contains a bare printed circuit board and like all products of this type, the user must be careful about the following points:

- The connection pins on the board might be sharp. Be careful when handling the board to avoid hurting yourself.
- This board contains static-sensitive devices. To avoid damaging it, handle the board in an ESD.proof environment.
- While powered, do not touch the electric connections on the board with your fingers or anything conductive. The board operates at a voltage level that is not dangerous, but components might be damaged when shorted.
- Do not put any liquid on the board and avoid operating the board close to water or at a high humidity level.
- Do not operate the board if it is dirty or dusty.

Hardware layout and configuration 5

The 32F746GDISCOVERY Discovery board is designed around the STM32F746NGH6 microcontroller (216-pin in TFBGA package). The hardware block diagram (see Figure 2) illustrates the connections between STM32F746NGH6 and peripherals (SDRAM, quad-SPI flash memory, camera module, color LCD, USB OTG connectors, USART, Ethernet, audio, SPDIFRX, microSD™ card, ARDUINO® Uno shields, and embedded ST-LINK). Figure 3 and Figure 4 help users to locate these features on the Discovery board.

The mechanical dimensions of the Discovery board are shown in Figure 5.




Figure 2. Hardware block diagram

UM1907 Rev 6 11/46

5.1 The 32F746GDISCOVERY Discovery board layout

Audio codec SN 128-Mbit SDRAM 3.5mm 4Mx32 stereo jacks (IN and OUT) I²C extension connector STM32F746NGH6 TFBGA216 SPDIF input, RCA connector RJ45 single port DCMI camera connector High-Speed USB PHY-ULPI Headers (ARDUINO®) 128-Mbit Quad-SPI, Quad/Dual ES CN3 USB Micro-AB connectors microSD™ card connector USB Type-B ST-LINK/V2-1 Headers (ARDUINO®) Power supply Power supply Push-buttons inlet 5V selector (user and reset) MSv38850V3

Figure 3. 32F746GDISCOVERY Discovery board top layout






Figure 4. 32F746GDISCOVERY Discovery board bottom layout

5.2 32F746GDISCOVERY Discovery board mechanical drawing




Figure 5. Mechanical drawing

Plastic spacer height = 15 mm, Overall height = 23 mm +/- 1 mm.



5.3 Embedded ST-LINK/V2-1

The ST-LINK/V2-1 programming and debugging tool is integrated on the 32F746GDISCOVERY Discovery board. Compared to ST-LINK/V2 the changes are listed below.

The new features supported on ST-LINK/V2-1 are:

- USB software reenumeration
- Virtual COM port interface on USB
- Mass storage interface on USB
- USB power management requests for more than 100 mA power on USB

These features are no longer supported on ST-LINK/V2-1:

- SWIM interface
- Application voltage lower than 3 V

For all general information concerning debugging and programming features common between V2 and V2-1 refer to *ST-LINK/V2 in-circuit debugger/programmer for STM8 and STM32* user manual (UM1075).

5.3.1 Drivers

Before connecting the 32F746GDISCOVERY board to a Windows® PC (7, 8, and 10) through the USB, a driver for the ST-LINK/V2-1 must be installed. It is available at the www.st.com website. In case the STM32 Discovery is connected to the PC before the driver is installed, some Discovery interfaces might be declared as <code>Unknown</code> in the PC device manager. To recover from this situation, after installing the dedicated driver, the association of "Unknown" USB devices found on the 32F746GDISCOVERY board to this dedicated driver, must be updated in the device manager manually.

Note: It is recommended to proceed by using the USB Composite Device, as shown in Figure 6.




Figure 6. USB composite device



UM1907 Rev 6 15/46

5.3.2 ST-LINK/V2-1 firmware upgrade

The ST-LINK/V2-1 embeds a firmware upgrade mechanism for in-place upgrade through the USB port. The firmware might evolve during the lifetime of the ST-LINK/V2-1 product (for example new functionality, bug fixes, and support for new microcontroller families). It is recommended to visit the *www.st.com* website before starting to use the 32F746GDISCOVERY board and periodically, to stay up to date with the latest firmware version.

5.4 Power supply

The 32F746GDISCOVERY Discovery board is designed to be powered by a 5V DC power supply. It is possible to configure the Discovery board to use any of the following five sources for the power supply:

 5V DC power adapter connected to JP2 (external power supply on the silkscreen of JP1 (5 V ext)). In this case, the 32F746GDISCOVERY Discovery board must be powered by a power supply unit or by an auxiliary equipment complying with the EN 62368-1:2014+A11:2017 standard, and must be safety extralow voltage (SELV) with limited power capability (see *Figure* 7).

5V ext 5V link usb fs 5V sv JP2 GND 5V JP1

Figure 7. JP1 (5V ext) from JP2 (5V)

 7-12 V DC power from CN6 pin named Vin on the silkscreen, the extension connectors for ARDUINO[®] Uno shields or daughterboard (external power source on the silkscreen of JP1 (5 V ext)), see *Figure 8*.




Figure 8. JP1 (5V ext) from CN6 (Vin)

 5V DC power with limitation from CN14, the USB Type-B connector of ST-LINK/V2-1 (USB 5V power source on the silkscreen of JP1 (5V link)). It is the default setting. If the USB enumeration succeeds (as explained below), the ST-LINK 5V link power is enabled, by asserting the PWR_ENn signal. This pin is connected to a power switch (ST890), which powers the board. This power switch also features a current limitation to protect the PC in case of a short circuit on the board (more than 600 mA).

The 32F746GDISCOVERY Discovery board can be powered from the ST-LINK USB connector CN14 (5V link), but only the ST-LINK circuit has the power before USB enumeration because the host PC only provides 100 mA to the board at that time. During the USB enumeration, the 32F746GDISCOVERY board asks for 500 mA power to the host PC. If the host can provide the required power, the enumeration ends with a SetConfiguration command and then, the power transistor U8 (ST890) is switched ON, the red LED LD2 is turned ON, thus the 32F746GDISCOVERY board can consume no more than 500 mA of current. If the host is not able to provide the requested current, the enumeration fails. Therefore, the ST890 (U8) remains OFF and the STM32 part including the extension board is not powered. As a consequence, the red LED LD2 remains turned OFF. In this case, it is mandatory to use an external power supply (see Figure 9).

5V ext 5V link usb _fs usb _hs JP1

Figure 9. JP1 (5V link)

Note:

In case the board is powered by a USB charger, there is no USB enumeration, so the led LD2 remains set to OFF permanently and the board is not powered. Only in this specific case, the resistor R109 needs to be soldered, to allow the board to be powered anyway.

The LED LD2 is lit when the 32F746GDISCOVERY Discovery board is powered by the 5V correctly.


Caution:

Do not connect the PC to the ST-LINK (CN14) when R109 is soldered. The PC might be damaged or the board not powered correctly.




UM1907 Rev 6 17/46

5V DC power with 500 mA limitation from CN13, the USB OTG_FS Micro-AB connector (USB 5V power source on the silkscreen of JP1 (usb_fs)), see Figure 10.



5V DC power with 500 mA limitation from CN12, the USB OTG_HS Micro-AB connector (USB 5V power source on the silkscreen of JP1 (usb_hs)), see Figure 11.



5.5 Programming/debugging when the power supply is not from ST-LINK (5V link)

It is mandatory to power the board first using JP1 (5V ext) or (usb_hs) or (usb_fs), then connect the USB cable to the PC. Proceeding this way the enumeration succeeds thanks to the external power source.

The following power sequence procedure must be respected:

- Connect the jumper JP1 on (5V ext) or (usb_hs) or (usb_fs)
- 2. Connect the external power source to JP2 or CN6 or CN12 or CN13
- 3. Check that the red LED LD2 is turned ON
- 4. Connect the PC to USB connector CN14

If this order is not respected, V_{BUS} might power the Discovery board first from ST-LINK, and the following risks might be encountered:

- 1. If the board needs more than 500 mA, the PC might be damaged or limit the current. As a consequence, the board is not powered correctly.
- 2. 500 mA is requested at the enumeration, so there is a risk that the request is rejected and enumeration does not succeed if the PC cannot provide such a current.

5.6 Clock sources

Up to three clock sources as described below:

- X1, 24 MHz oscillator for the USB OTG_HS PHY and camera module (daughterboard)
- X2, 25 MHz oscillator for the STM32F746NGH6 microcontroller and Ethernet PHY
- X3, 32 kHz crystal for the STM32F746NGH6 embedded RTC

5.7 Reset sources

The reset signal of the 32F746GDISCOVERY Discovery board is active at a low level and the reset sources include:

- Reset button B2
- ARDUINO® Uno shield board from CN6
- Embedded ST-LINK/V2-1

5.8 Audio

An audio codec WM8994ECS/R from CIRRUS with four DACs and two ADCs is connected to the SAI interface of the STM32F746NGH6 microcontroller. It communicates with STM32F746NGH6 via I^2 C bus shared with the camera module and I^2 C extension connector.

- The analog line input is connected to the ADC of WM8994ECS/R through the blue audio jack CN11.
- The analog line output is connected to the DAC of WM8994ECS/R via the green audio jack CN10.
- Two external speakers can be connected to WM8994ECS/R via JP3 for the right speaker and JP4 for the left speaker.
- Two digital microphones (ST-MEMS microphone) are on the 32F746GDISCOVERY Discovery board. They are connected to the input digital microphones of WM8994ECS/R.
- One coaxial connector CN1 is implemented on 32F746GDISCOVERY to receive external audio data compatible with the SPDIF specification.

5.9 USB OTG_FS

The 32F746GDISCOVERY Discovery board supports USB OTG full-speed communication via a USB Micro-AB connector (CN13) and a USB power switch (U6) connected to V_{BUS} . This USB connection can power the Discovery board at 5 V DC with a 500 mA current limitation.

A green LED LD5 lights up in one of these cases:

- The power switch (U6) is ON and 32F746GDISCOVERY works as a USB Host
- V_{BUS} is powered by another USB host when 32F746GDISCOVERY works as a USB device.

The red LED LD6 lights up when an overcurrent occurs.

Note: The 32F746GDISCOVERY must be powered by ar

The 32F746GDISCOVERY must be powered by an external power supply when using the OTG function.

5.10 USB OTG_HS

The 32F746GDISCOVERY Discovery board supports the USB OTG high-speed communication via a USB Micro-AB connector (CN12), USB high-speed PHY (U15) USB3320C-EZK from MICROCHIP for high-speed function.

The Discovery board can be powered by the USB connectors (CN12) at 5V DC with a 500 mA current limitation.

A USB power switch (U7) is also connected to V_{BUS} and provides power to CN12.

The green LED LD4 is lit in one of these cases:

- The power switch (U17) is ON and 32F746GDISCOVERY works as a USB host
- V_{BUS} is powered by another USB host when 32F746GDISCOVERY works as a USB device.

The red LED LD3 is lit when an overcurrent occurs.

Note: The 32F746GDISCOVERY board must be powered by an external power supply when using the OTG function.

5.11 microSD™ card

The 32F746GDISCOVERY board supports the 2-Gbyte (or more) microSD™ card connected to the SDMMC1 port of STM32F746NGH6.

4

5.12 Ethernet

The 32F746GDISCOVERY Discovery board supports 10/100-Mbit Ethernet communication by a PHY LAN8742A-CZ-TR (U9) from MICROCHIP and RJ45 jack (CN9). Ethernet PHY is connected to STM32F746NGH6 via the RMII interface.

The X2 oscillator generates the 25-MHz clock for the PHY, while the PHY RMII_REF_CLK generates the 50-MHz clock for STM32F746NGH6.




Figure 12. Inside RJ45 jack

5.13 SDRAM memory

The 128-Mbit SDRAM is connected to the FMC interface of the STM32F746NGH6 microcontroller. Only the lowest 16-bit data is used (64-Mbit accessible). DQ16 to DQ31 are unused and connected to a 10K ohm pull-down resistor.

5.14 Quad-SPI NOR flash memory

The 128-Mbit quad-SPI NOR flash memory is connected to the quad-SPI interface of the STM32F746NGH6 microcontroller.

47/

21/46

5.15 Camera module

A connector P1 with the DCMI signals is available to connect a camera module such as STM32F4DIS-CAM (ST order code).

5.16 Display LCD-TFT

The 4.3" 480x272 LCD-TFT with a capacitive touch panel is connected to the RGB LCD interface of the STM32F746NGH6 microcontroller.



UM1907 Connectors

6 Connectors

6.1 I²C extension connector CN2

Figure 13. I²C extension connector CN2 (front view)




Table 3. I²C extension connector CN2

| Pin number | Description | Pin number | Description |
|------------|---------------|------------|-------------|
| 1 | I2C_SDA (PB9) | 5 | +3V3 |
| 2 | NC | 6 | NC |
| 3 | I2C_SCL (PB8) | 7 | GND |
| 4 | RESET(PC10) | 8 | NC or 5V |

6.2 Camera module connector P1

Figure 14. Camera module connector P1 (front view)




Table 4. Camera module connector P1

| Pin number | Description | Pin number | Description |
|------------|-------------|------------|-------------|
| 1 | GND | 16 | GND |
| 2 | NC | 17 | DCMI_HSYNC |
| 3 | NC | 18 | NC |
| 4 | DCMI_D0 | 19 | DCMI_VSYNC |
| 5 | DCMI_D1 | 20 | 3V3 |

Connectors UM1907

Table 4. Camera module connector P1 (continued)

| Pin number | Description | Pin number | Description |
|------------|-------------|------------|----------------------|
| 6 | DCMI_D2 | 21 | Camera_CLK (OSC_24M) |
| 7 | DCMI_D3 | 22 | NC |
| 8 | DCMI_D4 | 23 | GND |
| 9 | DCMI_D5 | 24 | NC |
| 10 | DCMI_D6 | 25 | DCMI_PWR_EN |
| 11 | DCMI_D7 | 26 | DCMI_NRST |
| 12 | NC | 27 | DCMI_SDA |
| 13 | NC | 28 | DCMI_SCL |
| 14 | GND | 29 | GND |
| 15 | DCMI_PIXCK | 30 | 3V3 |

6.3 ARDUINO® Uno V3 connectors

CN4, CN5, CN6, and CN7 are female connectors compatible with ARDUINO $^{\$}$ standard. Most shields designed for ARDUINO $^{\$}$ can fit to the 32F746GDISCOVERY Discovery board.

The ARDUINO $^{\otimes}$ connectors on the 32F746GDISCOVERY Discovery board support the ARDUINO $^{\otimes}$ Uno V3 (see *Table 5*).

Caution: The I/Os of the STM32 microcontroller are 3.3 V compatible instead of 5 V for ARDUINO®

Uno.

UM1907 Connectors

Table 5. ARDUINO® connectors (CN4, CN5, CN6, and CN7)

| Left connectors | | | | | Right co | onnectors | | | |
|-----------------|------------|-------------|------------------------------|---|-------------------------|--------------|-------------|------------|--------|
| CN No. | Pin No. | Pin name | STM32 pin | Function | Function | STM32 pin | Pin name | Pin No. | CN |
| | | | | | I2C1_SCL | PB8 | D15 | 10 | |
| | | | | | I2C1_SDA | PB9 | D14 | 9 | |
| | | | | | AVDD | - | AREF | 8 | |
| | | | | | Ground | - | GND | 7 | |
| | 1 | NC | - | - | SPI2_SCK | PI1 | D13 | 6 | |
| | 2 | IOREF | - | 3.3V Ref | SPI2_MISO | PB14 | D12 | 5 | CN |
| | 3 | RESET | NRST | RESET | TIM12_CH2, SPI2_MOSI | PB15 | D11 | 4 | digi |
| CN6 power | 4 | +3V3 | - | 3.3V input/output | TIM1_CH1 | PA8 | D10 | 3 | |
| | 5 | +5V | - | 5V output | TIM2_CH1 | PA15 | D9 | 2 | |
| | 6 | GND | - | Ground | - | PI2 | D8 | 1 | |
| | 7 | GND | - | Ground | | • | - | | |
| | 8 | VIN | - | Power input | - | PI3 | D7 | 8 | |
| | • | - | | | TIM12_CH1 | PH6 | D6 | 7 | |
| | 1 | A0 | PA0 | ADC3_IN0 | TIM5_CH4,SPI 2_NSS | PI0 | D5 | 6 | |
| | 2 | A1 | PF10 | ADC3_IN8 | - | PG7 | D4 | 5 | |
| | 3 | A2 | PF9 | ADC3_IN7 | TIM3_CH1 | PB4 | D3 | 4 | |
| | 4 | A3 | PF8 | ADC3_IN6 | - | PG6 | D2 | 3 | CN |
| CN5 analog | 5 | A4 | PF7 or PB ⁽¹⁾ | ADC3_IN5 (PF7) or I2C1_SDA (PB9) | USART6_TX | PC6 | D1 | 2 | - digi |
| | 6 | A5 | PF6 or PB8 ⁽¹⁾ | ADC3_IN4 (PC0) or I2C1_SCL (PB8) | USART6_RX | PC7 | D0 | 1 | |

^{1.} Refer to *Table 12* for details.

Connectors UM1907

6.4 USB OTG_HS Micro-AB connector CN12

Figure 15. USB OTG Micro-AB connector CN12 (front view)





Table 6. USB OTG HS Micro-AB CN12

| Pin number | Description | Pin number | Description |
|------------|-------------|------------|-------------|
| 1 | VBUS | 4 | ID |
| 2 | D- | 5 | GND |
| 3 | D+ | - | - |

6.5 Ethernet RJ45 connector CN9

Figure 16. Ethernet RJ45 connector CN9 (front view)



UM1907 Connectors

Table 7. RJ45 connector CN9

| Pin number | Description | Pin number | Description |
|------------|---------------|------------|--------------|
| 1 | A, yellow LED | 7 | RD+ |
| 2 | K, yellow LED | 8 | RD- |
| 3 | TD+ | 9 | NC |
| 4 | TD- | 10 | GND |
| 5 | CT, 3V3 | 11 | K, green LED |
| 6 | CT, 3V3 | 12 | A, green LED |

6.6 USB OTG_FS Micro-AB connector CN13

Figure 17. USB OTG Micro-AB connector CN13 (front view)




Table 8. USB OTG FS Micro-AB connector CN13

| Pin number | Description | Pin number | Description |
|------------|-------------|------------|-------------|
| 1 | VBUS (PA9) | 4 | ID (PA10) |
| 2 | D- (PA11) | 5 | GND |
| 3 | D+ (PA12) | - | - |

Connectors UM1907

6.7 microSD™ connector CN3




Figure 18. microSD connector CN3 (front view)


Table 9. microSD connector CN3

| Pin number | Description | Pin number | Description |
|------------|-----------------|------------|---------------------------|
| 1 | SDMMC_D2 (PC10) | 6 | VSS/GND |
| 2 | SDMMC_D3 (PC11) | 7 | SDMMC_D0 (PC8) |
| 3 | SDMMC_CMD (PD2) | 8 | SDMMC_D1 (PC9) |
| 4 | +3.3V | 9 | GND |
| 5 | SDMMC_CK (PC12) | 10 | MicroSDcard_detect (PC13) |

6.8 ST-LINK/V2-1 USB Type-B connector CN14

The USB connector CN14 is used to connect the embedded ST-LINK/V2-1 to the PC for programming and debugging the STM32F746NGH6 microcontroller.

Figure 19. USB Type-B connector CN14 (front view)



UM1907 Connectors

Table 10. USB Type-B connector CN14

| Pin number | Description | Pin number | Description |
|------------|--------------|------------|-------------|
| 1 | VBUS (power) | 4 | GND |
| 2 | DM | 5, 6 | Shield |
| 3 | DP | - | - |

6.9 Audio stereo speakers JP3 and JP4

The stereo audio output JP3 and JP4 are available to support the stereo speakers (left and right).

6.10 Audio green jack (line out) CN10

A 3.5 mm stereo audio green jack output CN10 is available to support headphones.

6.11 Audio blue jack (line in) CN11

A 3.5 mm stereo audio blue jack input CN11 is available to support the audio-line input.

6.12 SPDIF input RCA connector CN1

Table 11. SPDIF input RCA connector CN1

| Pin number | Description | Pin number | Description |
|------------|-----------------|------------|-------------|
| 1 | SPDIF_RX0 (PD7) | 2 | GND |
| 2 | GND | - | - |

7 32F746GDISCOVERY I/O assignment

Table 12. 32F746GDISCOVERY I/O assignment

| Pin No. | Pin Name | Signal or Label | Comment |
|---------|----------|--------------------|------------------|
| A1 | PE4 | LTDC_B0 | - |
| A2 | PE3 | OTG_HS_OverCurrent | - |
| A3 | PE2 | QUADSPI_BK1_IO2 | - |
| A4 | PG14 | ETH_TXD1 | - |
| A5 | PE1 | FMC_NBL1 | - |
| A6 | PE0 | FMC_NBL0 | - |
| A7 | PB8 | ARDUINO SCL/D15 | - |
| A8 | PB5 | USB_OTG_HS_ULPI_D7 | - |
| A9 | PB4 | ARDUINO PWM/D3 | - |
| A10 | PB3 | SYS_JTDO-SWO | - |
| A11 | PD7 | SPDIF_RX0 | - |
| A12 | PC12 | SDMMC_CK | - |
| A13 | PA15 | ARDUINO PWM/D9 | - |
| A14 | PA14 | SYS_JTCK-SWCLK | - |
| A15 | PA13 | SYS_JTMS-SWDIO | - |
| B1 | PE5 | DCMI_D6 | - |
| B2 | PE6 | DCMI_D7 | - |
| В3 | PG13 | ETH_TXD0 | - |
| B4 | PB9 | ARDUINO SDA/D14 | - |
| B5 | PB7 | VCP_RX | - |
| В6 | PB6 | QUADSPI_BK1_NCS | - |
| В7 | PG15 | FMC_SDNCAS | - |
| B8 | PG11 | ETH_TX_EN | - |
| В9 | PJ13 | LTDC_B1 | - |
| B10 | PJ12 | OTG_FS_VBUS | (1) |
| B11 | PD6 | Audio_INT | - |
| B12 | PD0 | FMC_D2_DA2 | - |
| B13 | PC11 | SDMMC_D3 | - |
| B14 | PC10 | SDMMC_D2 | - |
| B15 | PA12 | USB_OTG_FS_DP | - |
| C1 | VBAT | - | Connected to VDD |
| C2 | PI8 | NC1 | - |

Table 12. 32F746GDISCOVERY I/O assignment (continued)

| Pin No. | Pin Name | Signal or Label | Comment |
|---------|---------------|----------------------|---------------------|
| C3 | PI4 | SAI2_MCLK_A | - |
| C4 | PK7 | LTDC_DE | - |
| C5 | PK6 | LTDC_B7 | - |
| C6 | PK5 | LTDC_B6 | - |
| C7 | PG12 | LTDC_B4 | - |
| C8 | PG10 | SAI2_SD_B | - |
| C9 | PJ14 | LTDC_B2 | - |
| C10 | PD5 | OTG_FS_PowerSwitchOn | - |
| C11 | PD3 | DCMI_D5 | - |
| C12 | PD1 | FMC_D3_DA3 | - |
| C13 | PI3 | ARDUINO D7 | - |
| C14 | PI2 | ARDUINO D8 | - |
| C15 | PA11 | USB_OTG_FS_DM | - |
| D1 | PC13 | uSD_Detect | - |
| D2 | PF0 | FMC_A0 | - |
| D3 | PI5 | SAI2_SCK_A | - |
| D4 | PI7 | SAI2_FS_A | - |
| D5 | PI10 | LTDC_HSYNC | - |
| D6 | PI6 | SAI2_SD_A | - |
| D7 | PK4 | LTDC_B5 | - |
| D8 | PK3 | LCD_BL_CTRL | - |
| D9 | PG9 | DCMI_VSYNC | - |
| D10 | PJ15 | LTDC_B3 | - |
| D11 | PD4 | OTG_FS_OverCurrent | - |
| D12 | PD2 | SDMMC_CMD | - |
| D13 | PH15 | TP3 | - |
| D14 | PI1 | ARDUINO SCK/D13 | - |
| D15 | PA10 | USB_OTG_FS_ID | - |
| E1 | PC14/OSC32_IN | RCC_OSC32_IN | - |
| E2 | PF1 | FMC_A1 | - |
| E3 | PI12 | LCD_DISP | - |
| E4 | PI9 | LTDC_VSYNC | - |
| E5 | PDR_ON | - | Connected to PU R38 |
| E6 | воото | - | Connected to PD R45 |
| E7 | VDD | - | - |



UM1907 Rev 6 31/46

Table 12. 32F746GDISCOVERY I/O assignment (continued)

| Pin No. | Pin Name | Signal or Label | Comment |
|---------|----------------|-------------------|------------------|
| E8 | VDD | - | - |
| E9 | VDD | - | - |
| E10 | VDD | - | - |
| E11 | VCAP_2 | - | Connected to C48 |
| E12 | PH13 | DCMI_PWR_EN | - |
| E13 | PH14 | DCMI_D4 | - |
| E14 | PI0 | ARDUINO PWM/CS/D5 | - |
| E15 | PA9 | VCP_TX | (1) |
| F1 | PC15/OSC32_OUT | RCC_OSC32_OUT | - |
| F2 | VSS | - | - |
| F3 | PI11 | B_USER | - |
| F4 | VDD | - | - |
| F5 | VDD | - | - |
| F6 | VSS | - | - |
| F7 | VSS | - | - |
| F8 | VSS | - | - |
| F9 | VSS | - | - |
| F10 | VSS | - | - |
| F11 | VDD | - | - |
| F12 | PK1 | LTDC_G6 | - |
| F13 | PK2 | LTDC_G7 | - |
| F14 | PC9 | SDMMC_D1 | - |
| F15 | PA8 | ARDUINO PWM/D10 | - |
| G1 | PH0/OSC_IN | RCC_OSC_IN | - |
| G2 | PF2 | FMC_A2 | - |
| G3 | PI13 | LCD_INT | - |
| G4 | PI15 | LTDC_R0 | - |
| G5 | VDD | - | - |
| G6 | VSS | - | - |
| G10 | VSS | - | - |
| G11 | VDDUSB | - | Connected to VDD |
| G12 | PJ11 | LTDC_G4 | - |
| G13 | PK0 | LTDC_G5 | - |
| G14 | PC8 | SDMMC_D0 | - |
| G15 | PC7 | ARDUINO RX/D0 | - |

Table 12. 32F746GDISCOVERY I/O assignment (continued)

| Pin No. | Pin Name | Signal or Label | Comment |
|---------|-------------|---------------------|----------------|
| H1 | PH1/OSC_OUT | RCC_OSC_OUT | - |
| H2 | PF3 | FMC_A3 | - |
| НЗ | PI14 | LTDC_CLK | - |
| H4 | PH4 | USB_OTG_HS_ULPI_NXT | - |
| H5 | VDD | - | - |
| H6 | VSS | - | - |
| H10 | VSS | - | - |
| H11 | VDD | - | - |
| H12 | PJ8 | LTDC_G1 | - |
| H13 | PJ10 | LTDC_G3 | - |
| H14 | PG8 | FMC_SDCLK | - |
| H15 | PC6 | ARDUINO TX/D1 | - |
| J1 | NRST | - | Hardware RESET |
| J2 | PF4 | FMC_A4 | - |
| J3 | PH5 | FMC_SDNWE | - |
| J4 | PH3 | FMC_SDNE0 | - |
| J5 | VDD | - | - |
| J6 | VSS | - | - |
| J10 | VSS | - | - |
| J11 | VDD | - | - |
| J12 | PJ7 | LTDC_G0 | - |
| J13 | PJ9 | LTDC_G2 | - |
| J14 | PG7 | ARDUINO D4 | - |
| J15 | PG6 | ARDUINO D2 | - |
| K1 | PF7 | ARDUINO A4 | - |
| K2 | PF6 | ARDUINO A5 | - |
| K3 | PF5 | FMC_A5 | - |
| K4 | PH2 | NC2 | - |
| K5 | VDD | - | - |
| K6 | VSS | - | - |
| K7 | VSS | - | - |
| K8 | VSS | - | - |
| K9 | VSS | - | - |
| K10 | VSS | - | - |
| K11 | VDD | - | - |



Table 12. 32F746GDISCOVERY I/O assignment (continued)

| Pin No. | Pin Name | Signal or Label | Comment |
|---------|------------|---------------------|---------------------|
| K12 | PJ6 | LTDC_R7 | - |
| K13 | PD15 | FMC_D1_DA1 | - |
| K14 | PB13 | USB_OTG_HS_ULPI_D6 | - |
| K15 | PD10 | FMC_D15_DA15 | - |
| L1 | PF10 | ARDUINO A1 | - |
| L2 | PF9 | ARDUINO A2 | - |
| L3 | PF8 | ARDUINO A3 | - |
| L4 | PC3 | FMC_SDCKE0 | - |
| L5 | BYPASS_REG | - | Connected to PD R20 |
| L6 | VSS | - | - |
| L7 | VDD | - | - |
| L8 | VDD | - | - |
| L9 | VDD | - | - |
| L10 | VDD | - | - |
| L11 | VCAP_1 | - | Connected to C47 |
| L12 | PD14 | FMC_D0_DA0 | - |
| L13 | PB12 | USB_OTG_HS_ULPI_D5 | - |
| L14 | PD9 | FMC_D14_DA14 | - |
| L15 | PD8 | FMC_D13_DA13 | - |
| M1 | VSSA | - | Connected to GND |
| M2 | PC0 | USB_OTG_HS_ULPI_STP | - |
| M3 | PC1 | ETH_MDC | - |
| M4 | PC2 | USB_OTG_HS_ULPI_DIR | - |
| M5 | PB2/BOOT1 | QUADSPI_CLK | - |
| M6 | PF12 | FMC_A6 | - |
| M7 | PG1 | FMC_A11 | - |
| M8 | PF15 | FMC_A9 | - |
| M9 | PJ4 | LTDC_R5 | - |
| M10 | PD12 | QUADSPI_BK1_IO1 | - |
| M11 | PD13 | QUADSPI_BK1_IO3 | - |
| M12 | PG3 | EXT_RST | - |
| M13 | PG2 | RMII_RXER | - |
| M14 | PJ5 | LTDC_R6 | - |
| M15 | PH12 | DCMI_D3 | - |
| N1 | VREF- | - | Connected to GND |

Table 12. 32F746GDISCOVERY I/O assignment (continued)

| Pin No. | Pin Name | Signal or Label | Comment |
|---------|----------|--------------------|--------------------|
| N2 | PA1 | ETH_REF_CLK | - |
| N3 | PA0/WKUP | ARDUINO A0 | - |
| N4 | PA4 | DCMI_HSYNC | - |
| N5 | PC4 | ETH_RXD0 | - |
| N6 | PF13 | FMC_A7 | - |
| N7 | PG0 | FMC_A10 | - |
| N8 | PJ3 | LTDC_R4 | - |
| N9 | PE8 | FMC_D5_DA5 | - |
| N10 | PD11 | QUADSPI_BK1_IO0 | - |
| N11 | PG5 | FMC_A15_BA1 | - |
| N12 | PG4 | FMC_A14_BA0 | - |
| N13 | PH7 | I2C3_SCL | - |
| N14 | PH9 | DCMI_D0 | - |
| N15 | PH11 | DCMI_D2 | - |
| P1 | VREF+ | - | Connected to VDDA |
| P2 | PA2 | ETH_MDIO | - |
| P3 | PA6 | DCMI_PIXCK | - |
| P4 | PA5 | USB_OTG_HS_ULPI_CK | - |
| P5 | PC5 | ETH_RXD1 | - |
| P6 | PF14 | FMC_A8 | - |
| P7 | PJ2 | LTDC_R3 | - |
| P8 | PF11 | FMC_SDNRAS | - |
| P9 | PE9 | FMC_D6_DA6 | - |
| P10 | PE11 | FMC_D8_DA8 | - |
| P11 | PE14 | FMC_D11_DA11 | - |
| P12 | PB10 | USB_OTG_HS_ULPI_D3 | - |
| P13 | PH6 | ARDUINO PWM/D6 | - |
| P14 | PH8 | I2C3_SDA | - |
| P15 | PH10 | DCMI_D1 | - |
| R1 | VDDA | - | Connected to VREF+ |
| R2 | PA3 | USB_OTG_HS_ULPI_D0 | - |
| R3 | PA7 | ETH_CRS_DV | - |
| R4 | PB1 | USB_OTG_HS_ULPI_D2 | - |
| R5 | PB0 | USB_OTG_HS_ULPI_D1 | - |
| R6 | PJ0 | LTDC_R1 | - |



UM1907 Rev 6 35/46

Table 12. 32F746GDISCOVERY I/O assignment (continued)

| Pin No. | Pin Name | Signal or Label | Comment |
|---------|----------|-----------------|---------|
| R7 | PJ1 | LTDC_R2 | - |
| R8 | PE7 | FMC_D4_DA4 | - |
| R9 | PE10 | FMC_D7_DA7 | - |
| R10 | PE12 | FMC_D9_DA9 | - |
| R12 | PE13 | FMC_D10_DA10 | - |
| R11 | PE15 | FMC_D12_DA12 | - |

^{1.} By default OTG_FS_VBUS is driven by the software and not by the alternate function of the STM32F746NGH6 (R64 = ON, R63 = OFF, R58 = ON and PA9 = VCP_TX (Virtual Com Port) and PJ12 = OTG_FS_VBUS).

To use the alternate function OTG_FS_VBUS of the STM32F746NGH6, it is needed to have: R64 = OFF, R63 = ON, R58 = OFF. In this configuration, VCP_TX is no longer available and PA9 = OTG_FS_VBUS, PJ12 = not connected.

8 32F746GDISCOVERY information

8.1 Product marking

The product and each board composing the product are identified with one or several stickers. The stickers, located on the top or bottom side of each PCB, provide product information:

 Main board featuring the target device: product order code, product identification, serial number, and board reference with revision.
 Single-sticker example:

Product order code
Product identification
syywwxxxxx
MBxxxx-Variant-yzz



Dual-sticker example:

Product order code Product identification

and | IVI

MBxxxx-Variant-yzz syywwxxxxx



Other boards if any: board reference with revision and serial number.
 Examples:











On the main board sticker, the first line provides the product order code, and the second line the product identification.

On all board stickers, the line formatted as "MBxxxx-Variant-yzz" shows the board reference "MBxxxx", the mounting variant "Variant" when several exist (optional), the PCB revision "y", and the assembly revision "zz", for example B01. The other line shows the board serial number used for traceability.

Products and parts labeled as "ES" or "E" are not yet qualified or feature devices that are not yet qualified. STMicroelectronics disclaims any responsibility for consequences arising from their use. Under no circumstances will STMicroelectronics be liable for the customer's use of these engineering samples. Before deciding to use these engineering samples for qualification activities, contact STMicroelectronics' quality department.

"ES" or "E" marking examples of location:

- On the targeted STM32 that is soldered on the board (for an illustration of STM32 marking, refer to the STM32 datasheet Package information paragraph at the www.st.com website).
- Next to the evaluation tool ordering part number that is stuck or silk-screen printed on the board.

Some boards feature a specific STM32 device version, which allows the operation of any bundled commercial stack/library available. This STM32 device shows a "U" marking option at the end of the standard part number and is not available for sales.

To use the same commercial stack in their applications, the developers might need to purchase a part number specific to this stack/library. The price of those part numbers includes the stack/library royalties.



UM1907 Rev 6 37/46

8.2 32F746GDISCOVERY product history

Table 13. Product history

| Order code | Product identification | Product details | Product change description | Product limitations |
|------------|------------------------|--|--------------------------------|---------------------|
| | 32F746GDISCO/ | MCU: - STM32F746NGH6 revision "Z" | Initial revision No limitation | |
| | | MCU errata sheet: - STM32F74xxx and STM32F75xxx device limitations (ES0290) | | No limitation |
| | | Board: - MB1191-F746NGH6- B02 or MB1191- F746NGH6-B03 or MB1191-F746NGH6- B04 | | |
| STM3 | 32F746GDISEM/ | MCU: - STM32F746NGH6 revision "Z" | | |
| | | MCU errata sheet: - STM32F74xxx and STM32F75xxx device limitations (ES0290) | Main board revision changed | No limitation |
| | | Board: – MB1191-F746NGH6- B05 | | |
| | DK32F746G\$CU1 | MCU: - STM32F746NGH6 revision "Z" | | |
| | | MCU errata sheet: - STM32F74xxx and STM32F75xxx device limitations (ES0290) | Main board revision changed | No limitation |
| | | Board: – MB1191-F746NGH6- C01 | | |

Table 13. Product history (continued)

| Order code | Product identification | Product details | Product change description | Product limitations |
|------------------|------------------------|--|---|---------------------|
| | DK32F746G\$CU2 | MCU: - STM32F746NGH6 revision "Z" | Main board revision changed | No limitation |
| | | MCU errata sheet: - STM32F74xxx and STM32F75xxx device limitations (ES0290) | | |
| | | Board: – MB1191-F746NGH6- C02 | | |
| STM32F746G-DISCO | DK32F746G\$CU3 | MCU: - STM32F746NGH6 revision "Z" | | No limitation |
| | | MCU errata sheet: - STM32F74xxx and STM32F75xxx device limitations (ES0290) | Packaging: plastic blister replaced by a carton box | |
| | | Board: – MB1191-F746NGH6- C02 | | |
| | DK32F746G\$CU4 | MCU: STM32F746NGH6 revision "Z" | | |
| | | MCU errata sheet: - STM32F74xxx and STM32F75xxx device limitations (ES0290) | Main board revision changed | No limitation |
| | | Board: – MB1191-F746NGH6- C03 | | |



8.3 Board revision history

Table 14. Board revision history

| Board reference | Board variant and revision | Board change description | Board limitations |
|------------------------|----------------------------|---|-------------------|
| | F746NGH6-B02 | Initial revision | No limitation |
| | F746NGH6-B03 | Changing the footprint of RCA connector CN1 | No limitation |
| | F746NGH6-B04 | Changing the footprint of the header JP2 Changing the footprint of MicroSD connector CN3 | No limitation |
| | F746NGH6-B05 | Memory Micron N25Q128A13EF840F is replaced by MT25QL128ABA1EW9-0SIT without impact on firmware | No limitation |
| MB1191 (main board) | F746NGH6-C01 | LCD Rocktech RK043FN48H-CT672B replaced by Kunjian HT043C without impact on firmware Memory MICRON MT48LC4M32B2B5 replaced by ISSI IS42S32400F-6BL without impact on firmware Several part references updated due to obsolescence (such as microphones or others, refer to the bill of materials for details) | No limitation |
| | F746NGH6-C02 | LCD Kunjian HT043C replaced by GJX GJX043A6-40DY without impact on firmware | No limitation |
| | F746NGH6-C03 | Memory MICRON MT25QL128ABA1EW9-0SIT replaced by WINBOND ELECTRONICS W25Q128JVEIQ with impact on firmware | No limitation |

9 Federal Communications Commission (FCC) and ISED Canada Compliance Statements

9.1 FCC Compliance Statement

Part 15.19

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Part 15.21

Any changes or modifications to this equipment not expressly approved by STMicroelectronics may cause harmful interference and void the user's authority to operate this equipment.

Part 15.105

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instruction, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception which can be determined by turning the equipment off and on, the user is encouraged to try to correct interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Note: Use only shielded cables.

Responsible party - U.S. contact information

Francesco Doddo STMicroelectronics, Inc. 200 Summit Drive | Suite 405 | Burlington, MA 01803 USA

Telephone: +1 781-472-9634



UM1907 Rev 6 41/46

9.2 **ISED Compliance Statement**

Compliance Statement

ISED Canada ICES-003 Compliance Label: CAN ICES-3 (B) / NMB-3 (B).

Déclaration de conformité

Étiquette de conformité à la NMB-003 d'ISDE Canada : CAN ICES-3 (B) / NMB-3 (B).

UM1907 Rev 6 42/46

UM1907 Product disposal

10 Product disposal

Disposal of this product: WEEE (Waste Electrical and Electronic Equipment)

(Applicable in Europe)



This symbol on the product, accessories, or accompanying documents indicates that the product and its electronic accessories must not be disposed of with household waste at the end of their working life.

To prevent possible harm to the environment and human health from uncontrolled waste disposal, separate these items from other types of waste and recycle them responsibly at a designated collection point to promote the sustainable reuse of material resources.

Household users:

Contact the retailer that you purchased the product from or your local authority for details of your nearest designated collection point.

Business users:

Contact your dealer or supplier for further information.



UM1907 Rev 6 43/46

Revision history UM1907

Revision history

Table 15. Document revision history

| Date | Revision | Changes | |
|-------------|----------|--|--|
| 12-Jun-2015 | 1 | Initial release. | |
| 02-Nov-2015 | 2 | Updated cover page adding mbed-enabled logo. Added: - Section 1: Features - Section 5: Demonstration software - Section 2: Product marking - Section 6: Ordering information - Section 7: Technology partners - Section Appendix B: Compliance Statements Updated Section 10: Electrical schematics figure 19 until the figure 31. Updated Section 7.4: Power supply. Updated Section 7.3.1: Drivers. | |
| 22-Mar-2016 | 3 | Updated Section Appendix B: Compliance Statements. | |
| 02-Jun-2017 | 4 | Updated: - Section 7.2: 32F746GDISCOVERY Discovery board mechanical drawing - Table 4: ARDUINO® connectors (CN4, CN5, CN6, and CN7) - Table 11: 32F746GDISCOVERY I/O assignment | |

UM1907 Revision history

Table 15. Document revision history (continued)

| Date | Revision | Changes | |
|-------------|----------|---|--|
| 13-Jan-2020 | 5 | Revised and reorganized Sections Introduction, Features, Ordering information, Product marking, System requirements, Development toolchains and Demonstration software. Updated Figure 1: 32F746GDISCOVERY board (top view: left side - bottom view: right side). Added Section 2: Codification. Added Section 3: Development environment Updated Figure 2: Hardware block diagram, Figure 3: 32F746GDISCOVERY Discovery board top layout and Figure 4: 32F746GDISCOVERY Discovery board bottom layout. Removed product references in Section 4.8: Audio, Section 4.13: SDRAM memory, Section 4.14: Quad-SPI NOR flash memory and Section 4.16: Display LCD-TFT. Removed Section 7: Technology partners and Section 10 Electrical schematics. | |
| 08-Sep-2025 | 6 | Updated: - Section 1: Features - Section 3.4: EDA resources - Section 9.1: FCC Compliance Statement Added: - Safety recommendations - 32F746GDISCOVERY information with updated Product marking, and new Product history and Board revision history tables - Product disposal Removed all references to Arm Mbed ™. | |

45/46

IMPORTANT NOTICE - READ CAREFULLY

STMicroelectronics NV and its subsidiaries ("ST") reserve the right to make changes, corrections, enhancements, modifications, and improvements to ST products and/or to this document at any time without notice.

In the event of any conflict between the provisions of this document and the provisions of any contractual arrangement in force between the purchasers and ST, the provisions of such contractual arrangement shall prevail.

The purchasers should obtain the latest relevant information on ST products before placing orders. ST products are sold pursuant to ST's terms and conditions of sale in place at the time of order acknowledgment.

The purchasers are solely responsible for the choice, selection, and use of ST products and ST assumes no liability for application assistance or the design of the purchasers' products.

No license, express or implied, to any intellectual property right is granted by ST herein.

Resale of ST products with provisions different from the information set forth herein shall void any warranty granted by ST for such product.

If the purchasers identify an ST product that meets their functional and performance requirements but that is not designated for the purchasers' market segment, the purchasers shall contact ST for more information.

ST and the ST logo are trademarks of ST. For additional information about ST trademarks, refer to www.st.com/trademarks. All other product or service names are the property of their respective owners.

Information in this document supersedes and replaces information previously supplied in any prior versions of this document.

© 2025 STMicroelectronics - All rights reserved